

### MODELS

#### *Compaq Smart Array 5i Controller*

---

##### Smart Array 5i Controller Option Kit

226593-B21

226593-291 (Japan)

### KEY PRODUCT FEATURES

Increased performance over the Integrated Smart Array Controller

- More robust and easier to use than software-based RAID
- Available standard on the *ProLiant™* DL380 Generation 2 (G2) server. Also available as an optional upgrade for the ProLiant ML370 Generation 2 (G2) server.
- Embedded hardware RAID controller
- Wide *Ultra3™* SCSI
- Compatibility with all *Ultra2™* and Ultra3 LVD family products. In addition, a seamless upgrade to next generation Compaq entry level or high performance mainstream Ultra3 Smart Array controllers.
- 32-bit architecture
- Dual SCSI channels (one internal and one external)
- Recovery ROM protects against a ROM image corruption

### OVERVIEW

The new Smart Array 5i Controller is an intelligent array controller for entry-level, hardware-based fault tolerance for protection of OS, applications, and logs. Dual Ultra3 SCSI channels (one internal and one external) allow you to support all Ultra2 and/or Ultra3 SCSI internal hard disk drives as well as support up to 14 Ultra2 and/or Ultra3 SCSI external hard disk drives using the *StorageWorks™* Enclosure 4300 Family by Compaq. The Smart Array 5i controller provides one of the most cost effective alternatives to software-based RAID in the market today. Designed and integrated with Compaq ProLiant DL380 Generation (G2) server, the Smart Array 5i controller provides worry-free data protection for all server internal storage needs (optional upgrade for the ProLiant ML370 Generation (G2) server).

### Target Environments

---

The Smart Array 5i Controller offers excellent investment protection in the following environments:

- **Non-RAID:** Current storage operations where, until now, there has not been a perceived need for data protection, security, or performance gains.
- **Software RAID:** Current storage operations using software RAID where growing data storage requirements demand the robustness, efficiency, and performance increases available with entry-level hardware RAID.

# COMPAQ

### OVERVIEW *(continued)*

#### The Smart Array Advantage

---

Compaq's innovative design and integration work of the Smart Array family of products creates customer value that is unmatched in the industry. Use of Smart Array products across multiple applications results in a much lower Total Cost of Ownership (TCO) than any other server storage RAID products. The Compaq Smart Array family brings an unparalleled return on investment through:

- **Data Compatibility** - among all models of Smart Array controllers allows simple and easy upgrades any time needs for higher performance, capacity, and availability increase. Even successive generations of Smart Array controllers understand the data format of other Smart Array Controllers.

**Note:** You cannot upgrade from the Integrated Smart Array Controller to the Smart Array 5i Controller because the Integrated Smart Array Controller is embedded on the system board and cannot be removed. However, any hard drives on the Integrated Smart Array Controller can be moved to another server that has the Smart Array 5i Controller and that data would be seamlessly recognized.

- **Consistent Configuration and Management Tools** – across the entire family of Smart Array controllers minimizes Total Cost of Ownership (TCO) by reducing training requirements and technical expertise necessary to install and maintain the Compaq server storage.
- **Universal Hard Drive** - form factor is for use across multiple Compaq servers, disk enclosures and storage systems. With compatibility across many enterprise platforms, you are free to deploy and re-deploy these drives to quickly deliver increased storage capacity, migrate data between systems, and easily manage spare drives.
- **Pre-Failure Warranty** - means Compaq *Insight Manager*™ not only reports when a drive is going to fail but allows replacement of failing drives prior to actual failure. For complete details, consult the Compaq Support Center or refer to your Compaq Server documentation.

### PRODUCT HIGHLIGHTS

#### Data Compatibility

---

Data compatibility among all models of Smart Array Controllers means customers can instantly upgrade their Smart Array products to get to higher performance, capacity and availability. Unlike competitive products, successive generations of Smart Array products understand the data format of other Smart Array controllers, providing investment protection for your Compaq storage solution.

**Note:** You cannot upgrade from the Integrated Smart Array Controller to the Smart Array 5i Controller because the Integrated Smart Array Controller is embedded on the system board and cannot be removed. However, any hard drives on the Integrated Smart Array Controller can be moved to another server that has the Smart Array 5i Controller and that data would be seamlessly recognized.

#### Availability

---

Provides increased server uptime by providing advanced storage functionality:

- Online RAID Level Migration (between any RAID level)
- Online Capacity Expansion
- Logical Drive Capacity Extension
- Global Online Spare
- Pre-Failure Warranty

#### Fault Prevention

---

The following features offer detection of possible failures before they occur, allowing preventive action to be taken:

- S.M.A.R.T.: Self Monitoring Analysis and Reporting Technology first developed at Compaq detects possible hard disk failure before it occurs, allowing replacement of the component before failure occurs.
- Drive Parameter Tracking monitor's drive operational parameters, predicting failure and notifying the administrator.
- Dynamic Sector Repairing continually performs background surface scans on the hard disk drives during inactive periods and automatically re-maps bad sectors, ensuring data integrity.
- Environment Tracking for External Storage System monitors

### PRODUCT HIGHLIGHTS *(continued)*

#### Fault Tolerance

---

Keeps data available and server running while a failed drive is being replaced; several fault tolerance configurations are supported including:

- **Distributed Data Guarding (RAID 5):** This allocates parity data across multiple drives and allows simultaneous write operations. It is recommended for up to 14 hard drives.
- **Drive Mirroring (RAID 1, 1+0):** This allocates half of the drive array to data and the other half to mirrored data, providing two copies of every file. It is a high-performance RAID.

#### Fault Recovery

---

Minimizes downtime, reconstructs data, and facilitates a quick recovery from drive failure

- **Recovery ROM:** This new feature provides a unique redundancy feature that protects from a ROM image corruption. A new version of firmware can be flashed to the ROM while the controller maintains the last known working version of firmware. If the firmware becomes corrupt, the controller will revert back to the previous version of firmware and continue operating. This reduces the risk of flashing firmware to the controller.
- **On-Line Spares:** Up to two spare drives can be installed prior to drive failure. If a failure occurs, recovery begins with an On-Line Spare and data is reconstructed automatically.

Note: On-Line Spares can only be used with RAID level 1, 1+0, and 5.

#### Ease of Use

---

Consistency and Upgradability make the Smart Array family unique in the industry:

- GUI based configuration, management and diagnostic software tools
- Common data format between generations of products
- Data migration between servers and external storage enclosures

### COMPATIBILITY

#### Servers

---

Available standard on the ProLiant DL380 Generation 2 (G2) server. Also available as an optional upgrade for the ProLiant ML370 Generation 2 (G2) server. For up to date Smart Array compatibility and support information, visit:

[ftp://ftp.compaq.com/pub/products/storageworks/array-and-scsi-controllers/SA\\_hardware\\_Compatibility.pdf](ftp://ftp.compaq.com/pub/products/storageworks/array-and-scsi-controllers/SA_hardware_Compatibility.pdf)

#### Operating Systems

---

- NT® 4.0 Server
- NT 4.0 Enterprise Edition
- NT 4.0 Terminal Server
- Microsoft® Windows® 2000
- Windows 2000 Advanced Server
- NetWare® 4.2\*
- NetWare 5.x
- Linux® RedHat® 7.0, 7.1
- Caldera® OpenLinux 2.3.1 and 3.1
- UnixWare® 7.x
- *OpenServer™* 5.x\*\*
- *Solaris™*\*\*\*
- OS/2\*\*

\*NetWare 4.11 with SupportPack 9 is supported.

\*\*Future support planned for ProLiant ML370 G2 servers

\*\*\*Future support planned

Note: Your server may not be supported on all operating systems listed.

For an up to date server OS support matrix, please consult: <ftp://ftp.compaq.com/pub/products/servers/os-support-matrix-310.pdf>

### COMPATIBILITY *(continued)*

#### Software Suite

---

All Smart Array products share a common set of configuration, management and diagnostic tools, including Array Configuration Utility (ACU), Array Diagnostic Utility (ADU), and Compaq Insight Manager XE. This software consistency of tools reduces the cost of training for each successive generation of product and takes much of the guesswork out of troubleshooting field problems. These tools lower the total cost of ownership by reducing training and technical expertise necessary to install and maintain the Compaq server storage.

#### Compaq Insight Manager XE

- Powerful server and server options/storage manager tool
- Monitors over 1200 server parameters

#### Configuration/Diagnostic Utilities

- Compaq Array Configuration Utility XE (ACU-XE)
  - Powerful Web based configuration utility for all Smart Array controllers
  - Provides a graphical view of Compaq drive array configurations
  - Allows for management of multiple arrays over a secure internet connection from anywhere in the world
  - Easy to use Wizards for configuration
  - Runs online on NT v4.0, Windows 2000 and NetWare
- Compaq Array Configuration Utility (ACU)
  - Powerful configuration utility for all Smart Array controllers
  - Provides a graphical view of Compaq drive array configurations
  - Easy to use Wizards for configuration
  - Runs online on NT v4.0, Windows 2000 and NetWare
- Options ROM Configuration for Arrays (ORCA)
  - Rapid configuration during initial install of the OS
- Compaq Array Diagnostic Utility (ADU)
  - Powerful diagnostic utility for all Smart Array controllers

#### Software

---

*SmartStart*™ 5.1 – Includes Array Configuration Utility XE (ACU-XE), Array Configuration Utility (ACU) and Compaq Insight Manager XE (CIM-XE).

# QuickSpecs

## Compaq Smart Array 5i Controller

### SPECIFICATIONS

#### Architecture

Protocol	Wide Ultra3 SCSI
Processor	32-bit RISC
XOR engine	Hardware RAID
Electrical interface	Low Voltage Differential (LVD)
Simultaneous Drive Transfer Channels	2
Channel Transfer Rate	320 MB/s total; 160 MB/s per channel
SCSI Port Connectors	One external and one internal SCSI port
Memory	32 MB of DRAM used for code, transfer buffers, and non-battery backed read cache
Peak transfer rate	160 MB/s
Logical Drives Supported	32
Software Upgradable Firmware	Yes
RAID Support	RAID 5 (Distributed Data Guarding) RAID 1+0 (Striping and Mirroring) RAID 1 (Mirroring) RAID 0 (Striping)
Disk Drive and Enclosure Protocol Support	Ultra2 and Ultra3

#### Option Kit Contents (for ProLiant ML370 Second Generation server)

- Field installable memory board (installs on server board)
- Support software CD
- User guide
- Warranty card

#### Warranty

- **Maximum:** The remaining warranty of the Compaq ProLiant server in which it is installed (to a maximum three-year, limited warranty)
- **Minimum:** One-year, on-site limited warranty

### OPTIONS

Hard Drives	<i>Wide Ultra3 SCSI Universal Drives – Hot Plug</i>	
	36.4-GB Wide Ultra3 SCSI 15,000 rpm Drive (1")	232916-B22
	18.2-GB Wide Ultra3 SCSI 15,000 rpm Drive (1")	188122-B22
	9.1-GB Wide Ultra3 SCSI 15,000 rpm Drive (1")	188120-B22
	72.8-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	232432-B22
	36.4-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	176496-B22
	18.2-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	142673-B22
	9.1-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	142671-B22
	36-GB Wide Ultra3 SCSI 10,000 rpm Drives (1"), 10 pack	232617-B21
	18-GB Wide Ultra3 SCSI 10,000 rpm Drives (1"), 10 pack	202352-B21
	<i>Wide Ultra3 SCSI Drives – Non-Hot Plug</i>	
	36.4-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	176497-B21
	18.2-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	142674-B21
	9.1-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	142672-B21
	Note: <b>This is a list of supported hard disk drives</b> (note that some drives may be discontinued).	

# QuickSpecs

## Compaq Smart Array 5i Controller

### OPTIONS *(continued)*

Software	<b>SANWorks™ Virtual Replicator</b>	
	Note: For additional Virtual Replicator ordering information refer to <a href="http://www.compaq.com/products/StorageWorks/swvr/swvrorderinfo.html">http://www.compaq.com/products/StorageWorks/swvr/swvrorderinfo.html</a> .	
	License & Media (CD-ROM)	191802-B21
Universal Hot Plug Tape Drives	Internal 20/40-GB DAT, Hot Plug	215488-B21
	Internal AIT 35-GB, LVD, Hot Plug	216886-B21
	Internal AIT 50-GB, Hot Plug	215487-B21
Storage Enclosures	Compaq <i>StorageWorks</i> Enclosure Model 4314T	190210-001
	Compaq <i>StorageWorks</i> Enclosure Model 4314T (Int'l)	190210-B31
	Compaq <i>StorageWorks</i> Enclosure Model 4314T (Japan)	190210-291
	Compaq <i>StorageWorks</i> Enclosure Model 4314R	190209-001
	Compaq <i>StorageWorks</i> Enclosure Model 4314R (Int'l)	190209-B31
	Compaq <i>StorageWorks</i> Enclosure Model 4314R (Japan)	190209-291
	Compaq <i>StorageWorks</i> Enclosure Model 4354R	190211-001
	Compaq <i>StorageWorks</i> Enclosure Model 4354R (Int'l)	190211-B31
	Compaq <i>StorageWorks</i> Enclosure Model 4354R (Japan)	190211-291
Related Products	Compaq Smart Array 532 Controller	225338-B21
	Compaq Smart Array 532 Controller (Japan)	225338-291
	Compaq Smart Array 5302/32 Controller	166207-B21
	Compaq Smart Array 5302/32 Controller (Japan)	166207-291
	Compaq Smart Array 5302/64 Controller	124992-B21
	Compaq Smart Array 5302/64 Controller (Japan)	124992-291
	Compaq Smart Array 5304/128 Controller	158939-B21
	Compaq Smart Array 5304/128 Controller (Japan)	158939-291

© 2002 Compaq Information Technologies Group, LP.

Compaq, the Compaq logo, Insight Manager, ProLiant, SANworks, SmartStart and StorageWorks are trademarks of Compaq Information Technologies Group, L.P. in the U.S. and/or other countries. Microsoft, Windows 2000, and Windows NT are trademarks of Microsoft Corporation in the U.S. and/or other countries. NetWare is a registered trademark of Novell Inc. Linux is a registered trademark of Linus Torvalds. RedHat is a trademark of RedHat, Inc., in the U.S. and other countries. Solaris, Ultra2 and Ultra3 are trademarks of Sun Microsystems, Inc. in the U.S. and other countries. Caldera and OpenServer are trademarks of Caldera International, Inc., in the U.S. and other countries. UnixWare is a trademark of The Open Group in the U.S. and/or other countries. All other product names mentioned herein may be trademarks of their respective companies.

Compaq shall not be liable for technical or editorial errors or omissions contained herein. The information is provided "as is" without warranty of any kind and is subject to change without notice. The warranties for Compaq products are set forth in the express limited warranty statements accompanying such products. Nothing herein should be construed as constituting an additional warranty.